
DUST COLLECTOR PREVENTIVE MAINTENANCE SCHEDULE



DAILY MAINTENANCE & OPERATION

Dust Collection Drum 1: Check level every day and empty if needed

WEEKLY MAINTENANCE

Cartridges: Check for alarm signal and adjust values displayed on the DCT1000 control panel (2)
Replace cartridges as needed (4)

MONTHLY MAINTENANCE

Ducting: Check for leaks and wear, replace as needed **Pulse Cleaning System:** inspect Goyen Valves **6**, and replace or service as needed

BI-ANNUAL MAINTENANCE

Motor (3): Check motor bearings Refer to name plate for oil type and volume required

REPLACE WHEN NEEDED

(about every 3 years)

DESCRIPTION	PART Nb
Basic Cartridges 4 (each)	601307
Nanofiber Cartridges 4 (each)	601317
Door Seal 5 (½" x 1") (sold by foot)	618305
1½" Goyen Valve Complete Assembly 6	601329
1½" Goyen Valve Repair Kit 6	M-2192



Controller Periodical
Adjustment
for required actions